

## P-LINK-4 (USB)

파워 계측용 PC 인터페이스. 4개 채널.



### 제품군 주요 특징

#### READS ALL POWER DETECTORS TYPES

Thermopiles and photo detectors of the PH100 & PH20 series

#### MULTI-CHANNEL CAPABILITIES

Available with 1 or 4 channels

#### PC-BASED

Connects to your PC with included software

#### SMALL SIZE

Only 91 mm (L) x 57 mm (W) x 36 (H)

#### SERIAL COMMANDS

Serial commands are available on both versions to let you take full control

#### REAL-TIME STATISTICAL FUNCTIONS

Max, min, average, standard deviation, RMS and PTP stability, pulse # and repetition rate

#### USB, RS-232 OR ETHERNET

Choose your favourite communications port. The USB version is port-powered. Ethernet available only on 4-channel version.

## 사양

### 컨트롤러 및 GUI 사양

디지털 디스플레이 사이즈	컴퓨터 화면
데이터 표시	Real time, ratio, line plot, histogram, statistics and 3D histogram
외부 트리거	없음
실시간 데이터 전송	10 Hz
시리얼 커맨드	USB
파워 미터 사양	
파워 범위(열전퇴)	3 $\mu$ W - 30 kW
파워 범위(광전다이오드)	1 pW - 3 W
모니터 정확성	$\pm$ 0.5%, 전체 범위
통계	현재값, 최대, 최소, 평균, 표준 편차, RMS 및 PTP 안정성, 시간
응답 시간	현재값, 최대, 최소, 평균, 표준 편차, RMS 및 PTP 안정성, 시간
에너지 미터 사양	
물리적 특성	
치수	286W x 233H x 43D mm
중량	2.5 kg
주문 정보	
P-LINK-4 (USB)	202223

Specifications are subject to change without notice. Refer to the user manual for complete specifications.

이 제품에 관심이 있으십니까?

견적받기

[gentec-eo.com/ko/contact-us](http://gentec-eo.com/ko/contact-us)에서 현지 영업 담당자를 찾으십시오.