

# **U-LINK (USB)**

PC interface for power & energy measurement. Single-channel, USB output.



### PRODUCT FAMILY KEY FEATURES

#### THE UNIVERSAL METER

Reads all heads:

- Power: thermopiles, photodetectors and pyroelectrics
- Energy: thermopiles (in single shot mode), photodetectors and pyroelectrics

### MEASURE FJ ENERGY LEVELS

Thanks to a unique digital method for suppressing the noise on the lower ranges

### **EXTERNAL TRIGGER**

Synchronize your U-LINK to your pulsed laser or digital chopper

### SERIAL COMMANDS

Serial commands are available on both versions to let you take full control

### **REAL-TIME STATISTICAL FUNCTIONS**

Max, min, average, standard deviation, RMS and PTP stability

### SYNCHRONIZE MULTIPLE CHANNELS

With the "SYNC. OUT" port, you can plug multiple U-LINK devices together and create a low-cost multi-channel system.

### **SPECIFICATIONS**

| Digital display size                    | Computer screen                                                                 |
|-----------------------------------------|---------------------------------------------------------------------------------|
| Data display                            | Real time, ratio, line plot, histogram, statistics and 3D histogram             |
| Analog output                           | 0-2 V, adjustable, full scale, ±1 %                                             |
| External trigger                        | 3.3 to 12 V                                                                     |
| Real-time data transfer                 | 10 kHz                                                                          |
| Serial commands via                     | USB                                                                             |
| External power supply                   | USB 5V, 150 mA                                                                  |
| POWER METER SPECIFICATIONS              |                                                                                 |
| Power range                             | 4 pW - 30 kW                                                                    |
| Digital resolution                      | 23 bits on current scale                                                        |
| Device accuracy                         | ±0.5 % ±3 μV                                                                    |
| Statistics                              | Current value, max, min, average, standard deviation, RMS & PTP stability, time |
| Response time                           | Current value, max, min, average, standard deviation, RMS & PTP stability, time |
| ENERGY METER SPECIFICATIONS             |                                                                                 |
| Energy range                            | 2 fJ to 30 kJ                                                                   |
| Digital resolution                      | Current Scale/3754                                                              |
|                                         |                                                                                 |
| Device accuracy                         | 1 % ±50 µV (< 500 Hz)<br>2 % ±50 µV (500 Hz - 10 kHz)                           |
| Device accuracy  Software trigger level |                                                                                 |
| ·                                       | 2 % ±50 µV (500 Hz - 10 kHz) 0.1 to 99.9 %, 0.1 % resolution, default 2 %       |
| Software trigger level                  | 2 % ±50 μV (500 Hz - 10 kHz)                                                    |

PHYSICAL CHARACTERISTICS

Dimensions 57W x 26H x 91D mm

Weight 0.12 kg

ORDERING INFORMATION

U-LINK (USB) 203510

Specifications are subject to change without notice. Refer to the user manual for complete specifications.

## **INTERESTED IN THIS PRODUCT?**



Find your local sales representative at gentec-eo.com/contact-us