## gentec-ۥ)

测量能力

### PRONTO-250-FLEX-Y

便携式激光功率计, 最高可达250 W。袖珍型热量计具有三种测量模式: SSP、CWP 和 SSE。



#### 产品系列主要特性

#### **NEW! THE FLEXIBILITY TO PICK THE CALIBRATIONS YOU NEED**

The PRONTO-250-FLEX offers three calibration options so you only pay for what you need:

- $\bullet$  Default calibration "Y": for visible to NIR wavelengths (248 nm to 2.5  $\mu$ m)
- Additional calibration "C": for CO<sub>2</sub> lasers (10.6 μm)
- Additional calibration "E": for energy measurements with ± 5 % accuracy

#### POCKET-SIZE

This mid to high power handheld probe is so compact it fits in your pocket!

#### **FASY-TO-USE**

The touchscreen color LCD allows for a friendly user interface. You can make a measurement with just the touch of a button!

#### **DATA LOGGING**

Save your data to the internal memory and then transfer it to your PC over the USB connection.

#### FROM LOW TO HIGH POWERS

Thanks to a low noise level and high damage threshold, the PRONTO-250-FLEX can measure powers from 0.5 W to 250 W.

#### HANDS-FREE OPERATION

Place it on a flat surface or use one of the 2 threaded holes that we have integrated in the casing for safe use with optical stands.

#### SERIAL COMMANDS

Serial commands are available to let you take full control of your PRONTO from your PC.

#### 兼容性支架

STAND-S-233

### 规格

侧里能力	
最大平均功率	250 W
最小平均功率	0.5 W
噪声等效功率	10 mW
光谱范围	0.193 - 20 µm
<b>典型升起</b> 时间	1.5 s
功率校准不确定性	±3 %
曝光时间	5 s
测量能力(能量模式)	
最大可测量能量	25 J
噪声等效能量	60 mJ
最小重复周期	4 s
最大脉冲宽度	88 ms
能量校准不确定性	±5 %
连续 <b>功率模式</b>	
<b>最大平均功率</b> (连续)	8 W

最大平均功率密度「	45 kW/cm²
最大允许外壳温度	65 °C
1. 1064 nm, 10 W CW。 May vary with wavelength and average power.	
控制器和图形用户界面 (GUI) 规格	
电池类型	<b>可充</b> 电锂电池
电池寿命	17 小时或 4200 次测量
显示分辨率	1 mW
显示屏尺寸	28.0 x 35.0 mm (128 x 160像素)
显示屏类型	彩色触屏
背后照明	可调节
网络升级方式	USB
数据存储	50,000 pts
电池充电方式	USB
物理特性	
孔径	19 mm
吸收器	Н9
尺寸	59.0W x 181.4L x 17.0D
重量	0.21 kg
安装孔	2 x 8-32
订购信息	
PRONTO-250-FLEX-Y	205654Y
PRONTO-250-FLEX-YC	205654YC
PRONTO-250-FLEX-YCE	205654YCE

1.5 s

**响**应时间

损坏阈

规格如有更改, 恕不另行通知。有关完整规格, 请参阅用户手册。

# 对这个产品感兴趣吗?

获**得**报**价** 

通过 gentec-eo.cn/contact-us 找到您的本地销售代表