

S-LINK-1

파워&에너지 계측용 PC 인터페이스. 단일채널, USB 출력.



제품군 주요 특징

- READS BOTH POWER AND ENERGY**
Thermopiles and pyroelectrics
- AVAILABLE WITH 1 OR 2 CHANNELS**
S-LINK-1 and S-LINK-2 models now available
- PC-BASED**
Connects to your PC with included software
- SERIAL COMMANDS**
Serial commands are available on all versions to let you take full control
- FASTEST DATA TRANSFER RATE**
Get all the points transferred directly into your PC at 10 kHz/Channel
- USB OR ETHERNET**
Choose your favourite communications port. The USB version is port-powered
- EXTERNAL TRIGGER**
Every model comes standard with a 2.4 V to 24 V external trigger

↓
사양

컨트롤러 및 GUI 사양	
디지털 디스플레이 사이즈	컴퓨터 화면
데이터 표시	Real time, ratio, line plot, histogram, statistics and 3D histogram
외부 트리거	3-24V @ 13mA, 광학적 절연
시리얼 커맨드	USB
파워 미터 사양	
모니터 정확성	±0.75%, 전체 범위의 10%
통계	현재값, 최대, 최소, 평균, 표준 편차, RMS 및 PTP 안정성, 시간
응답 시간	현재값, 최대, 최소, 평균, 표준 편차, RMS 및 PTP 안정성, 시간
에너지 미터 사양	
디지털 해상도	정상 모드: 현재 눈금/4096
모니터 정확성	±1 % (<500 Hz) ±2 % (500 Hz - 1.2 kHz) ±3 % (1.2 - 6 kHz) ±6 % (6 - 10 kHz)
반복률 ¹	10 kHz
실시간 데이터 전송 ²	정상 모드에서 10kHz/채널, 누락 포인트 없음
통계	현재값, 최대, 최소, 평균, 표준 편차, RMS 및 PTP 안정성, 펄스 번호, 반복률 및 평균 출력
물리적 특성	
치수	106W x 34H x 147D mm
중량	0.424 kg
주문 정보	
S-LINK-1	202225

1. 최대 반복 속도는 PC 및 감지기 속도에 따라 달라질 수 있습니다.
2. 실제 요금은 컴퓨터에 따라 다를 수 있습니다.

이 제품에 관심이 있으십니까?

견적받기

gentec-eo.com/ko/contact-us에서 현지 영업 담당자를 찾으십시오.