

## U-LINK (RS-232)

PC interface for power & energy measurement. Single-channel, RS-232 output.



### PRODUCT FAMILY KEY FEATURES

#### THE UNIVERSAL METER

Reads all heads:

- Power: thermopiles, photodetectors and pyroelectrics
- Energy: thermopiles (in single shot mode), photodetectors and pyroelectrics

#### MEASURE FJ ENERGY LEVELS

Thanks to a unique digital method for suppressing the noise on the lower ranges

#### SERIAL COMMANDS

Serial commands are available on both versions to let you take full control

#### REAL-TIME STATISTICAL FUNCTIONS

Max, min, average, standard deviation, RMS and PTP stability

## SPECIFICATIONS

### CONTROLLER AND GUI SPECIFICATIONS

Digital display size	Computer screen
Data display	Real time, ratio, line plot, histogram, statistics and 3D histogram
Analog output	0-2 V, adjustable, full scale, $\pm 1\%$
External trigger	None
Real-time data transfer	1 kHz
Serial commands via	RS-232
External power supply	9-12 V, 200 mA

### POWER METER SPECIFICATIONS

Power range	4 pW - 30 kW
Digital resolution	23 bits on current scale
Device accuracy	$\pm 0.5\%$ $\pm 3\mu\text{V}$
Statistics	Current value, max, min, average, standard deviation, RMS & PTP stability, time
Response time	Current value, max, min, average, standard deviation, RMS & PTP stability, time

### ENERGY METER SPECIFICATIONS

Energy range	2 fJ to 30 kJ
Digital resolution	Current Scale/3754
Device accuracy	1 % $\pm 50\mu\text{V}$ (< 500 Hz) 2 % $\pm 50\mu\text{V}$ (500 Hz - 10 kHz)
Software trigger level	0.1 to 99.9 %, 0.1 % resolution, default 2 %
Repetition rate <sup>1</sup>	10 kHz
Real-time data transfer	1 kHz with time stamp, no missing point
Statistics	Current value, max, min, average, standard deviation, RMS & PTP stability, pulse #, repetition rate and average power

1. Maximum repetition rate may vary with PC and detector speeds.

PHYSICAL CHARACTERISTICS

Dimensions57W x 26H x 91D mm

Weight0.105 kg

ORDERING INFORMATION

U-LINK (RS-232)203994B

Specifications are subject to change without notice. Refer to the user manual for complete specifications.

INTERESTED IN THIS PRODUCT?

GET A QUOTE

Find your local sales representative at [gentec-eo.com/contact-us](https://gentec-eo.com/contact-us)