

### QE25LP-H-MB-QED-D0

Pyroelectric detector for laser energy measurement up to 23 J.



#### PRODUCT FAMILY KEY FEATURES

#### MODULAR CONCEPT

Increase the power capability of your detector: 2 different cooling modules

#### LOW NOISE LEVEL

2 μJ for the MB coating

#### **QED ATTENUATOR AVAILABLE**

Measure up to 5X higher energies. Available with optional calibration, all wavelengths between 532 & 1064 nm, or single wavelength. Read more.

0.193 kg

#### HIGH REPETITION RATE OPTIONS

- QE25HR-MB: 1 000 Hz
- QE25HR-MT: 10 000 Hz

#### **TEST TARGET INCLUDED**

With the MB models

#### SMART INTERFACE

Containing all the calibration data

#### **COMPATIBLE STAND**

STAND-D-233

## **SPECIFICATIONS**

### MEASUREMENT CAPABILITIES

Spectral range <sup>1</sup>	0.3 - 2.1 µm
Typical rise time	550 µs
Repeatability	<0.5%
Maximum repetition frequency <sup>2</sup>	300 Hz
Maximum measurable energy <sup>3</sup>	23 J
Noise equivalent energy <sup>4</sup>	E µ3
Maximum pulse width	400 µs
Energy calibration uncertainty	±3 %

- 1. For the calibrated spectral range, see the user manual.
- $2. \ May be limited by the display or PC interface. Please refer to the corresponding user manual.\\$
- ${\it 3. At 1064}\ nm, {\it 7}\ ns, {\it 10}\ Hz.\ Increasing\ pulse\ width\ increases\ maximum\ measurable\ energy.$
- ${\it 4.}\ {\it Nominal value}. Actual value depends on electrical noise in the measurement system.$

#### DAMAGE THRESHOLDS

Maximum average power density <sup>1</sup>	600 W/cm²
Maximum energy density <sup>2</sup>	8 J/cm²
Maximum power	30 W

- 1. May vary with wavelength and average power.
- 2. At 1064 nm, 7 ns, 10 Hz. May vary with wavelength and pulse width.

#### PHYSICAL CHARACTERISTICS

Weight

FITISICAL CHARACTERISTICS	
Cooling	Convection (heatsink)
Aperture width	22 mm
Aperture height	22 mm
Absorber	QED
Dimensions	53H x 55W x 58D mm

ORDERING INFORMATION	
QE25LP-H-MB-QED-D0	202183
QE25LP-H-MB-QED-INT-D0	202734
QE25LP-H-MB-QED-INE-D0	
QE25LP-H-MB-QED-IDR-D0	203264

Specifications are subject to change without notice. Refer to the user manual for complete specifications.

# **INTERESTED IN THIS PRODUCT?**



Find your local sales representative at gentec-eo.com/contact-us