

# HP100A-12KW-HD-MET-D0

High power detector for laser power measurement up to 12000  $\rm W$ 



#### PRODUCT FAMILY KEY FEATURES

#### HIGH POWER HANDLING

Handles up to 30 kW of continuous power with our standard models. Custom models are available for higher powers (See SUPER HP).

#### STABLE READING

Less sensitive to variations in water cooling temperature than any other high-power water-cooled meter on the market

#### LARGE APERTURE

Our standard HP models (4KW, 12KW, 15KW and 30KW) have a very large effective aperture of up to 280 mm to accommodate even the largest laser beams. Larger apertures with various shapes are available upon request (See SUPER HP).

#### AVAILABLE WITH YAG AND CO2 CALIBRATION

All HP Models can be calibrated at YAG and  ${\rm CO_2}$  wavelengths with a calibration uncertainty of +/- 5%

#### DIRECT USB CONNECTION TO A PC

Each head comes with both a DB-15 connector (for use with a Gentec-EO monitor) and a USB2.0 output for direct connection to a PC.

#### **COMPATIBLE STAND**

STAND-S-443-C

## **SPECIFICATIONS**

### MEASUREMENT CAPABILITIES

Maximum average power (continuous)	12000 W
Minimum average power <sup>1</sup>	300 W
Noise equivalent power <sup>2</sup>	10 W
Spectral range	0.193 - 20 μm
Typical rise time	9 s
Typical power sensitivity	0.15 mV/W
Power calibration uncertainty	±5 %
Repeatability	±2 %
Back reflections	~ 15 %
Linearity with power	±1.5 %
Linearity vs beam diameter	±1 %
Linearity vs beam position <sup>3</sup>	±1.7 %

- 1. For lower powers, call your Gentec-EO representative.
- 2. Nominal value. Actual value depends on electrical noise in the measurement system.
- 3. For a beam size of 20% of the aperture area, moved across 80% of the aperture area.

### WATER REQUIREMENTS

Required cooling flow <sup>1</sup>	(6 - 10) LPM < ±1 LPM/min
Temperature range	15 – 25 °C
Rate of temperature change	< ±3°C/min
Maximum water pressure	413 kPa (60 psi)

1. Contact Gentec-EO for clean deionized water cooling module option.

#### DAMAGE THRESHOLDS

Maximum average power density<sup>1</sup> 16 kW/cm<sup>2</sup>

 $1.\,At\,1064\,nm, 1.07-1.08\,\mu m\,and\,10.6\,\mu m, 500\,W\,CW.\,Refer\,to\,user\,manual\,for\,damage\,threshold\,at\,other\,powers.\,May\,vary\,with\,wavelength\,and\,average\,power.\,May\,vary\,with\,wavelength\,and\,average\,power.\,May\,vary\,with\,wavelength\,and\,average\,power.\,May\,vary\,with\,wavelength\,and\,average\,power.\,May\,vary\,with\,wavelength\,and\,average\,power.\,May\,vary\,with\,wavelength\,and\,average\,power.\,May\,vary\,with\,wavelength\,and\,average\,power.\,May\,vary\,with\,wavelength\,and\,average\,power.\,May\,vary\,with\,wavelength\,and\,average\,power.\,May\,vary\,with\,wavelength\,and\,average\,power.\,May\,vary\,with$ 

Data display	Real time, scope, needle, averaging, histogram and statistics
Analog output <sup>1</sup>	0-2 Volts
Serial commands via	USE
External power supply <sup>2</sup>	Through USB or Gentec-EO displays & PC interfaces
Display type	None
1.12 V maximum output signal available upon request. 2. A USB power adaptor will be necessary if the HP is used with a DB-15 extension cable.	
. 12 V maximum output signal available upon request.	
. 12 V maximum output signal available upon request. 2. A USB power adaptor will be necessary if the HP is used with a DB-15 extension cable.	Wate
1.12 V maximum output signal available upon request. 2. A USB power adaptor will be necessary if the HP is used with a DB-15 extension cable.  PHYSICAL CHARACTERISTICS	Wate 100 mm
. 12 V maximum output signal available upon request.  2. A USB power adaptor will be necessary if the HP is used with a DB-15 extension cable.  PHYSICAL CHARACTERISTICS  Cooling	
. 12 V maximum output signal available upon request.  2. A USB power adaptor will be necessary if the HP is used with a DB-15 extension cable.  PHYSICAL CHARACTERISTICS  Cooling  Aperture diameter	100 mn

Specifications are subject to change without notice. Refer to the user manual for complete specifications.

201328M

HP100A-12KW-HD-MET-D0

## **INTERESTED IN THIS PRODUCT?**

GET A QUOTE

Find your local sales representative at gentec-eo.com/contact-us