

## MIRO ALTITUDE

파워&에너지 계측용 터치스크린 디스플레이 장치. 단일채널 다중 출력.



### 제품군 주요 특징

#### NEW: READS INTEGRA ALL-IN-ONE DETECTORS

With the [latest firmware update \(V1.01.00\)](#), MIRO ALTITUDE is now compatible with Gentec-EO's INTEGRA (USB) series.

- Power detectors: XLP, UP and PH series
- Energy detectors: QE series\*, UP and XLP series in energy mode

\*Except QE8 and PE detectors

#### A SCREEN DESIGNED FOR PROFESSIONAL USE

10" high-resolution, anti-glare touchscreen, just like one would expect nowadays for a professional work tool.

#### A USER INTERFACE THAT WON'T LEAVE YOU SEARCHING AROUND

With its modern and intuitive user interface, MIRO ALTITUDE is so simple to use that it is literally plug-and-play. It was designed to take full advantage of its larger-than-life screen so you can see at a glance all that matters to your measurement at all times.

#### SUPER STRONG AND DURABLE

Remarkably strong and durable metal casing that you won't be afraid to break in the field or during transportation.

#### CONNECTIVITY POSSIBILITIES

Support for analog output and external trigger, as well as USB keys to log data.

#### CONVENIENT WAYS TO USE IT

- Tabletop
- On a stand
- Handheld

#### DISPLAY MODES FOR ALL USE CASES

MIRO ALTITUDE has 3 display modes, including one that lets you time-travel to check past data points without interrupting the current measurement session, and another mode with extra large size digits that you can view from across the room.

#### FEATURING XNR ANTICIPATION™

Measure up to 10x faster (detector-dependant) with XNR Anticipation™, which is probably the fastest measuring capability ever brought to a measurement instrument in this industry.

#### BUILT-IN DATA VIEWER

View a recorded measurement session directly on your MIRO ALTITUDE.

#### BUILT-IN FILE MANAGER

Save and organize your recorded measurement sessions and screenshots or move your files to your USB stick.

#### READS MOST HEADS

MIRO ALTITUDE is compatible with almost all Gentec-EO power and energy detectors with the standard DB15 output.

- Power detectors: XLP, UP and PH series
- Energy detectors: QE series\*, UP and XLP series in energy mode

\*Except QE8 detectors

호환 스탠드

[STAND-R-443](#)

|  |   |
|--|---|
| 컨트롤러 및 GUI 사양                            | 217x136mm LCD - 1280x800 픽셀                                       |
| 데이터 표시                                   | Real time, scope, statistics, digital tuning needle and averaging |
| 아날로그 출력                                  | 0-1 볼트, 전체 범위, ±1%  |
| 외부 트리거                                   | 3.3-24V   |
| 데이터 저장                                   | Internal memory or USB key  |
| 배터리 유형                                   | Rechargeable Li-ion cell  |
| 배터리 수명                                   | 6시간   |
| 외부 전원                                    | 9-24 VDC 3.33 A, USB-C (min 18 W)                                 |
| 파워 미터 사양                                 |   |
| 모니터 정확성                                  | 0.5% ±3 μV, 전체 범위의 20%  |
| 통계                                       | 현재값, 최대, 최소, 평균, 표준 편차, RMS 및 PTP 안정성, 시간                         |
| 응답 시간                                    | 현재값, 최대, 최소, 평균, 표준 편차, RMS 및 PTP 안정성, 시간                         |
| 에너지 미터 사양                                |   |
| 모니터 정확성                                  | 1% ±50 μV (<500 Hz)<br>2% ±50 μV (500 Hz - 10 kHz)                |
| 소프트웨어 트리거 수준                             | 0.1~99.9%, 0.1% 해상도, 기본값 2%                                       |
| 반복률 <sup>1</sup>                         | 10 kHz  |
| 통계                                       | 현재값, 최대, 최소, 평균, 표준 편차, RMS 및 PTP 안정성, 펄스 번호, 반복률 및 평균 출력         |
| 1. 최대 반복 속도는 PC 및 감지기 속도에 따라 달라질 수 있습니다. |   |
| 물리적 특성                                   |   |
| 치수                                       | 268W x 196H x 36D mm  |
| 중량                                       | 1.36 kg   |
| 주문 정보                                    |   |
| MIRO ALTITUDE                            | 205516B   |

Specifications are subject to change without notice. Refer to the user manual for complete specifications.

## 이 제품에 관심이 있으십니까?

견적받기

[gentec-eo.com/ko/contact-us](http://gentec-eo.com/ko/contact-us)에서 현지 영업 담당자를 찾으십시오.