

P-LINK (RS-232)

파워 계측용 PC 인터페이스. 단일채널, RS-232 출력.



주요 특징

READS ALL POWER DETECTORS TYPES

Thermopiles and photo detectors of the PH100 & PH20 series

MULTI-CHANNEL CAPABILITIES

Available with 1 or 4 channels

PC-BASED

Connects to your PC with included software

SMALL SIZE

Only 91 mm (L) x 57 mm (W) x 36 (H)

SERIAL COMMANDS

Serial commands are available on both versions to let you take full control

REAL-TIME STATISTICAL FUNCTIONS

Max, min, average, standard deviation, RMS and PTP stability, pulse # and repetition rate

USB, RS-232 OR ETHERNET

Choose your favourite communications port. The USB version is port-powered. Ethernet available only on 4-channel version.

사양

컨트롤러 및 GUI 사양

디지털 디스플레이 사이즈	컴퓨터 화면
데이터 표시	Real Time, Ratio, Line Plot, Histogram, Statistics and 3D Histogram
아날로그 출력	0-2 볼트, 조절 가능, 전체 범위, ±1%
외부 트리거	없음
실시간 데이터 전송	10 Hz
시리얼 커맨드	RS-232
외부 전원	100/240 VAC 50-60Hz에서 9 VDC 1.66 A
파워 미터 사양	
파워 범위(열전퇴)	3 μW - 10 kW
파워 범위(광전다이오드)	1 nW - 3 W
모니터 정확성	±0.5%, 전체 범위
통계	현재값, 최대, 최소, 평균, 표준 편차, RMS 및 PTP 안정성, 시간
응답 시간	1 sec
에너지 미터 사양	
물리적 특성	
치수	57W x 26H x 91D mm
중량	0.12 kg
주문 정보	
P-LINK (RS-232)	200440B

이 제품에 관심이 있으십니까?

gentec-eo.com/ko/contact-us에서 현지 영업 담당자를 찾으십시오.