

APPLICATION NOTE

MAESTRO FIRMWARE UPDATE PROCEDURE



ALWAYS KEEP YOUR MAESTRO UP TO DATE TO TAKE ADVANTAGE OF ALL THE NEW FUNCTIONALITIES

FOLLOW THIS EASY STEP-BY-STEP UPDATE PROCEDURE

- Download the update file from the website at: <u>http://gentec-eo.com/downloads/software-firmware</u> in the Firmware tab
- 2. Save it to a known location on your PC (like your desktop)
- 3. Unzip the file:
 - 3.1 Locate the ZIP file on your computer
 - 3.2 Right-click on it and choose "Extract All..."
 - 3.3 Follow the instructions on the screen
 - 3.4 Locate the extracted folder and open it
 - 3.5 You should now see the BIN file



BEAM DIAGNOSTICS

OEM DETECTORS

SPECIAL PRODUCTS



APPLICATION NOTE

4. Copy the BIN file on a USB key, directly in the main folder (not in a sub-folder)

| 📕 C:\Users\User_Name_Folder\Desktop\Maestro-¥1.03.02 | | | | * B _ D X | |
|--|---------------------|------------|-----------------|-------------------------|--|
| Maestro-V1.03.02 | | | 👻 🛂 🛛 Search Ma | Search Maestro-V1.03.02 | |
| Eile Edit ⊻iew Tools Help Organize ▼ Include in library ▼ Share v | with 🔻 Burn New fol | der | | III 🕶 🗔 🔞 | |
| Name * | Date modified | Туре | Size | | |
| Maestro-V1.03.02.bin | 11/05/2012 9:06 A | M BIN File | 26,051 KB | | |

5. Plug the USB key in the MAESTRO



- 9. Wait for the MAESTRO to do the update sequence
- 10. When the reboot message appears, turn off the MAESTRO
- **11**. Wait a few seconds
- 12. Turn it on again and the update will be done
- If you want to check the update has been done, go in HOME About again and verify that the firmware version corresponds to the initial update file

2